

# ETP41

## 12V Top Terminal Battery Cabinet With Pull Out Trays



### Features:

- Ships fully assembled and wired for easy installation.
- UL 1778 listed and fully tested at the factory prior to shipping.
- Rugged battery tray design allows a fully loaded tray to be pulled out and rest in pulled position for easy battery access and maintenance.
- Battery trays and rails are designed with an intergrated stop.
- Removable hinged doors for easy battery access.
- Locking doors provide access security.
- Removable rear panel allows battery access from rear.
- Batteries secured with non-conductive strapping for safe transit.
- DC Circuit Breakers up to 600A available. Breaker options include: Shunt trips, auxiliary contacts and under voltage releases.
- Acid resistant powder coat finish using a five stage immersion pretreatment process.
- Front and rear access for standard pallet jack.
- NFPA 70 models- available.
- Seismic options available.

### Options:

- Additional Booster chargers available for longer run times.
- Spill containment systems options are available.
- Remote Battery Monitoring options are available.
- Custom colors are available to match existing equipment

### STANDARD CABINET SPECIFICATIONS

| WIDTH |      | DEPTH |     | HEIGHT |      | WEIGHT |     |
|-------|------|-------|-----|--------|------|--------|-----|
| in.   | mm   | in.   | mm  | in.    | mm   | lbs.   | Kg  |
| 40    | 1016 | 29.5  | 749 | 78.7   | 2000 | 825    | 374 |

### BATTERY CONFIGURATION TABLE

| BATTERY MODEL NUMBER | BATTERY MANUFACTURER |          |           |           |           |     | MAXIMUM NUMBER OF BATTERIES PER CABINET |
|----------------------|----------------------|----------|-----------|-----------|-----------|-----|---|
|                      | ENERSYS              | C & D    | EAST PENN | GNB       | NORTHSTAR | CSB |   |
| 12HX205              | UPS12-210MR          | 45HR2000 | S12V120   | NSB12-310 | HRL12200W | 60  |   |
|                      |                      |          | S12V170   |           |           |     |   |
| 12XH300              | UPS12-300MR          | HR3000   | S12V285   | NSB12-425 | HRL12280W | 40  |   |
|                      |                      |          | S12V300   |           |           |     |   |
| 12HX330              | UPS12-350MR          | HR3500   | S12V370   | NSB12-540 | HRL12330W |     |   |
| 12HX400              | UPS12-400MR          | HR4000   |           |           | HRL12390W |     |   |
| 12HX505              | UPS12-490MR          | 31HR5000 | S12V500   | HRL12500W |           |     |   |
| 12HX540              | UPS12-540MR          | HR5500   |           |           | NSB12-540 |     | HRL12540W                               |
|                      | UPS12-600MR          |          |           |           |           |     |   |
| 6HX800               | UPS6-620MR           |          | 6S740NGF  |           |           |     |   |