ETP36 12V Top Terminal Battery Cabinet With Pull Out Trays



Features:

- Ships fully assembled and wired for easy installation.
- UL 1778 listed and fully tested at the factory prior to shipping.
- Rugged battery tray design allows a fully loaded tray to be pulled out and rest in pulled position for easy battery access and maintenance.
- Battery trays and rails are designed with an intergrated stop.
- Removable hinged doors for easy battery access.
- Locking doors provide access security.
- Removable rear panel allows battery access from rear.
- Batteries secured with non-conductive strapping for safe transit.
- DC Circuit Breakers up to 600A available. Breaker options include: Shunt trips, auxiliary contacts and under voltage releases.
- Acid resistant powder coat finish using a five stage immersion pretreatment process.
- Front and rear access for standard pallet jack.
- NFPA 70 models- available.
- Seismic options available.

Options:

- Additional Booster chargers available for longer run times.
- Spill containment systems options are available.
- Remote Battery Monitoring options are available.
- Custom colors are available to match existing equipment

STANDARD CABINET SPECIFICATIONS

WIDTH		DEPTH		HEIGHT		WEIGHT	
in.	mm	in.	mm	in.	mm	lbs.	Kg
36	915	29.5	749	78.7	2000	700	317

BATTERY CONFIGURATION TABLE													
	ENERSYS	C & D	EAST PENN	GNB	NORTHSTAR	CSB	MAXIMUM NUMBER OF BATTERIES PER CABINET						
	12HX205	UPS12-210MR	45HR2000	\$12V120		HRL12200W	60						
ER	1287205	0F312-210WR	45882000	\$12V170									
UMB	12XH300	UPS12-300MR	HR3000	\$12V285	NSB12-310	HRL12280W	32						
Z	1224300			\$12V300									
EL	12HX330	UPS12-350MR	HR3500	S12V370	NSB12-425	HRL12330W							
MODI	12HX400	UPS12-400MR	HR4000			HRL12390W							
R	12HX505	UPS12-490MR	31HR5000	S12V500	NSB12-540	HRL12500W							
Ë	12017540	UPS12-540MR	UREEOO	3120500		HRL12540W							
BAT	12HX540	UPS12-600MR	HR5500	S12V550NGF									
	6HX800	UPS6-620MR		6S740NGF									

