

EFC16-S0S

16V Front Terminal Stand-by Battery Cabinet



Features:

- Nema 1 enclosure design
- Ships fully assembled and wired for easy installation
- Specifically designed for 16V Front Terminal Batteries
- 115/230 VAC input, 1-20 VDC / 1-20A output Charger
- Removable side panels and battery retainers for simple battery access and removal
- Each battery is cabled to fuse block with an Anderson connector harness for safe battery disconnect.
- Multiple battery configurations available depending on the battery size
- Acid resistant powder coat finish using a five stage immersion pretreatment process
- Seismic Zone 4 rated design

STANDARD CABINET SPECIFICATIONS

WIDTH		DEPTH		HEIGHT		WEIGHT	
in.	mm	in.	mm	in.	mm	lbs.	Kg
31.4	798	31.5	800	72.0	1829	580	263

Options:

- Other chargers are available.
- Monitoring options are available.
- Custom colors are available to match existing equipment

BATTERY CONFIGURATION TABLE

BATTERY CAPACITY	MAXIMUM NUMBER OF BATTERIES PER CABINET
550 WPC	24
800 WPC	16
925 WPC	16